

FirePro²

CONVENTIONAL FIRE ALARM PANEL
2, 4 & 8 ZONES



FirePro²

CONVENTIONAL FIRE ALARM PANEL - 2, 4 & 8 ZONES

General Specifications

- » Conventional Fire alarm panel
- » 2, 4 or 8 conventional zones
- » Active End of Line monitored zones
- » 4 monitored Siren/Relay outputs
- » Constant or ANSI sound output patterns
- » Universal Access Level 2 key (key code access as well)
- » Alarm verification with pre-alarm output. Configurable for each zone.
7 delay values
- » Day/Night operation (with external timer)
- » Output delays (7 values)
- » Cross zone (dual zone) alarms. Configurable on each zone pair (4 pairs on 8 zone model)
- » 24VDC Auxiliary output
- » 24VDC output, interruptible during reset (e.g. for gas detector reset)
- » Remote reset input
- » Bell (class change) input
- » Walk test (individual zone capable)
- » Repeater expansion port
- » TCP/IP module expansion port
- » Alarm and Fault/Disablement indicators for each zone



Product Codes

- SYS-7200** - 2 Zone Fire Panel
- SYS-7201** - 4 Zone Fire Panel
- SYS-7202** - 8 Zone Fire Panel
- SYS-7203** - LCD Keypad/Repeater
- SYS-7204** - TCP/IP Module
- SYS-7205** - RS232 Module for Repeater Connection

Technical Specifications

Mains Power	230 VAC / 50Hz
Zones input voltage (with EOL & AEOL)	16 to 21 V
Max Power	100 VA max input power
Battery placement	Two 7 Ah batteries will fit in the panel
Standby Power	5 VA
Auxiliary power output	24VDC 1.5Amp
Zone termination	22uF / 25V capacitors
Monitored output termination	47 KOhms resistors
Fire relay output	Dry contacts NO or NC selectable
Environmental	Temperature: -2 to 45 °C (32 to 120 °F) Humidity: 5 to 95% RH, non condensing
Panel's dimensions (HxWxD)	315 x 425 x 105mm
Semi flush wall mounting	25mm max height

Specifications are subject to change without notice



1293

EC Certificate Number
0040/101/1/2018
CPR Certificate Number
1293-CPR-0604



EU Fire & Security - Units 2-4, The Pavilions, Bridgefold Road, Rochdale, Greater Manchester OL11 5BY



01706 658 880



01706 658 918



www.eufireandsecurity.com



sales@eufireandsecurity.com